

BC-100 Conference Microphone Base

Key Features




- The BC-100 serves as three functions: connected with a gooseneck microphone to be a desktop conference microphone, a boundary microphone, and insert a MIPRO ACT-Series bodypack transmitter into the BC-100 base to be a wireless conference microphone.
- The rear panel has a balanced XLR connector with a switch to select the audio source from either the built-in boundary microphone or the optional gooseneck microphone.
- The housing is made of metal with a thicker and anti-slip bottom pad to give added stability.
- TALK / MUTE button provides easy speaking or mute option; a LED indicates status.

Transmitters & Microphones

ACT-T Series	Bodypack Transmitters
ACT-TC Series	Bodypack Transmitters
MM-204	Gooseneck Microphone (385 mm / 15.1 ")
MM-205	Gooseneck Microphone (485 mm / 19.1 ")
MM-206	Gooseneck Microphone (585 mm / 23 ")

Technical Specifications

Built-in Boundary Microphone	Ø 10 mm cardioid condenser microphone
Input Connector	4 pin XLR female
Output Connector	Balanced XLR male
TALK / MUTE Button	Mechanical PUSH-HOLD switch, with a LED status indicator
Power Supply	12 ~ 48 V DC phantom power is required (external cable)
Color	Black
Dimensions	100 × 58 × 150 mm (W × H × D)
Weight	Approx. 618 g



MIPRO Electronics Co., Ltd

Headquarters: 814 Beigang Road, Chiayi, 60096, Taiwan
Tel: +886.5.238.0809 | Fax: +886.5.238.0803
www.mipro.com.tw | mipro@mipro.com.tw